



US010403339B2

(12) **United States Patent**  
**Baker**

(10) **Patent No.:** **US 10,403,339 B2**  
(45) **Date of Patent:** **\*Sep. 3, 2019**

(54) **QUANTIZING CIRCUITS HAVING IMPROVED SENSING**

*11/5642* (2013.01); *G11C 11/5678* (2013.01);  
*G11C 13/0004* (2013.01); *G11C 2211/5634* (2013.01);

(71) Applicant: **Ovonyx Memory Technology, LLC**, Alexandria, VA (US)

(Continued)

(72) Inventor: **Russel J. Baker**, Boise, ID (US)

(58) **Field of Classification Search**

CPC .. *G11C 5/147*; *G11C 7/12*; *G11C 8/08*; *G11C 7/222*; *G11C 29/12005*; *G11C 7/1066*  
See application file for complete search history.

(73) Assignee: **Micron Technology, Inc.**, Boise, ID (US)

(56) **References Cited**

(\*) Notice: Subject to any disclaimer, the term of this patent is extended or adjusted under 35 U.S.C. 154(b) by 0 days.

U.S. PATENT DOCUMENTS

4,460,982 A 7/1984 Gee et al.  
5,218,569 A 6/1993 Banks

(Continued)

This patent is subject to a terminal disclaimer.

OTHER PUBLICATIONS

(21) Appl. No.: **16/184,798**

Rane Corporation, RaneNote 137, "Digital Charma of Audio A/D Converters," 1997, 12 pgs.

(22) Filed: **Nov. 8, 2018**

(Continued)

(65) **Prior Publication Data**

US 2019/0096456 A1 Mar. 28, 2019

Primary Examiner — Hien N Nguyen

**Related U.S. Application Data**

(74) Attorney, Agent, or Firm — Fletcher Yoder, P.C.

(60) Continuation of application No. 15/269,418, filed on Sep. 19, 2016, now Pat. No. 10,127,954, which is a (Continued)

(57) **ABSTRACT**

A system including a processor and a memory device. The memory device includes a memory array having a plurality of memory elements connected to a bit-line and a quantizing circuit. The quantizing circuit includes a combination circuit configured to combine an analog input signal with an analog feedback signal to produce a delta signal. The quantizing circuit also includes an integrator configured to receive and integrate the delta signal to produce a sigma signal. The quantizing circuit also includes an analog-to-digital converter configured to receive the sigma signal and compare the sigma signal with a reference signal to produce a digital output signal.

(51) **Int. Cl.**



*G11C 5/14* (2006.01)  
*G11C 7/22* (2006.01)  
*G11C 11/56* (2006.01)  
*G11C 7/16* (2006.01)  
*G11C 7/06* (2006.01)

(Continued)

(52) **U.S. Cl.**

CPC ..... *G11C 7/22* (2013.01); *G11C 5/147* (2013.01); *G11C 7/065* (2013.01); *G11C 7/16* (2013.01); *G11C 8/08* (2013.01); *G11C*

**20 Claims, 20 Drawing Sheets**



**Related U.S. Application Data**

continuation of application No. 15/074,759, filed on Mar. 18, 2016, now Pat. No. 9,449,664, which is a continuation of application No. 14/507,452, filed on Oct. 6, 2014, now Pat. No. 9,299,405, which is a division of application No. 14/076,908, filed on Nov. 11, 2013, now Pat. No. 8,854,899, which is a division of application No. 13/486,535, filed on Jun. 1, 2012, now Pat. No. 8,582,375, which is a division of application No. 12/951,997, filed on Nov. 22, 2010, now Pat. No. 8,194,477, which is a division of application No. 11/820,003, filed on Jun. 15, 2007, now Pat. No. 7,839,703.

(51) **Int. Cl.**

*GIIC 8/08* (2006.01)  
*GIIC 13/00* (2006.01)  
*H03M 3/00* (2006.01)

(52) **U.S. Cl.**

CPC ..... *GIIC 2211/5644* (2013.01); *H03M 3/43* (2013.01); *H03M 3/456* (2013.01)

(56)

**References Cited**

U.S. PATENT DOCUMENTS

5,600,319 A 2/1997 Ginetti  
 5,614,856 A 3/1997 Wilson et al.  
 5,627,784 A 5/1997 Roohparvar  
 5,748,535 A 5/1998 Lin et al.  
 5,953,276 A 9/1999 Baker  
 5,973,956 A 10/1999 Blyth et al.  
 6,044,019 A 3/2000 Cernea et al.  
 6,097,637 A 8/2000 Bauer et al.  
 6,188,340 B1 2/2001 Matsumoto et al.  
 6,282,120 B1 8/2001 Cernea et al.  
 6,466,476 B1 10/2002 Wong et al.  
 6,490,200 B2 12/2002 Cernea et al.  
 6,504,750 B1 1/2003 Baker  
 6,567,297 B2 5/2003 Baker  
 6,661,708 B2 12/2003 Cernea et al.  
 6,664,708 B2 12/2003 Shlimak et al.  
 6,665,013 B1 12/2003 Fossum et al.  
 6,741,502 B1 5/2004 Cernea  
 6,781,906 B2 8/2004 Perner et al.  
 6,785,156 B2 8/2004 Baker  
 6,795,359 B1 9/2004 Baker  
 6,798,705 B2 9/2004 Baker  
 6,807,403 B2 10/2004 Tanaka  
 6,813,208 B2 11/2004 Baker  
 6,822,892 B2 11/2004 Baker  
 6,826,102 B2 11/2004 Baker  
 6,829,188 B2 12/2004 Choi  
 6,847,234 B2 1/2005 Mokhlesi et al.  
 6,850,441 B2 2/2005 Baker  
 6,856,564 B2 2/2005 Baker  
 6,870,784 B2 3/2005 Baker  
 6,901,020 B2 5/2005 Doerrer et al.  
 6,909,394 B2 6/2005 Baker  
 6,914,838 B2 7/2005 Baker  
 6,930,942 B2 8/2005 Baker  
 6,954,390 B2 10/2005 Baker  
 6,954,391 B2 10/2005 Fletcher et al.  
 6,977,601 B1 12/2005 Baker  
 6,985,375 B2 1/2006 Hush et al.  
 7,002,833 B2 2/2006 Baker  
 7,009,901 B2 3/2006 Baker  
 7,095,667 B2 8/2006 Baker  
 7,102,932 B2 9/2006 Baker  
 7,133,307 B2 11/2006 Combe et al.  
 7,151,701 B2 12/2006 Taylor et al.  
 7,366,021 B2 4/2008 Baker  
 7,538,702 B2 5/2009 Baker  
 7,667,632 B2 2/2010 Baker

7,768,868 B2 8/2010 Baker  
 7,817,073 B2 10/2010 Baker  
 8,194,477 B2 6/2012 Baker  
 9,449,664 B2 9/2016 Baker  
 10,127,954 B2\* 11/2018 Baker  
 2002/0101758 A1 8/2002 Baker  
 2002/0194557 A1 12/2002 Park  
 2003/0039162 A1 2/2003 Baker  
 2003/0043616 A1 3/2003 Baker  
 2003/0067797 A1 4/2003 Baker  
 2003/0198078 A1 10/2003 Baker  
 2003/0214868 A1 11/2003 Baker  
 2004/0008555 A1 1/2004 Baker  
 2004/0032760 A1 2/2004 Baker  
 2004/0062100 A1 4/2004 Baker  
 2004/0076052 A1 4/2004 Baker  
 2004/0095839 A1 5/2004 Baker  
 2004/0190327 A1 9/2004 Baker  
 2004/0190334 A1 9/2004 Baker  
 2004/0199710 A1 10/2004 Baker  
 2004/0240294 A1 12/2004 Baker  
 2005/0002249 A1 1/2005 Baker  
 2005/0007803 A1 1/2005 Baker  
 2005/0007850 A1 1/2005 Baker  
 2005/0013184 A1 1/2005 Baker  
 2005/0018477 A1 1/2005 Baker  
 2005/0018512 A1 1/2005 Baker  
 2005/0041128 A1 2/2005 Baker  
 2005/0088892 A1 4/2005 Baker  
 2005/0088893 A1 4/2005 Baker  
 2005/0201145 A1 9/2005 Baker  
 2006/0013040 A1 1/2006 Baker  
 2006/0062062 A1 3/2006 Baker  
 2006/0221696 A1 10/2006 Li  
 2006/0227641 A1 10/2006 Baker  
 2006/0250853 A1 11/2006 Taylor et al.  
 2006/0291291 A1 12/2006 Hosono et al.  
 2008/0095213 A1 4/2008 Lin et al.  
 2008/0297388 A1 12/2008 Thiagarajan et al.  
 2008/0309530 A1 12/2008 Baker  
 2008/0309534 A1 12/2008 Baker  
 2008/0310236 A1 12/2008 Baker  
 2012/0243343 A1 9/2012 Baker

OTHER PUBLICATIONS

Baker, R.J., (2001-2006) *Sensing Circuits for Resistive Memory*, presented at various universities and companies.  
 Baker, "CMOS Mixed Signal Circuit Design," IEEE Press, A. John Wiley & Sons, Inc.; Copyright 2003, Figures 30.63, 31.82, 32.6, 32.7, 32.24, 32.51, 33.34, 33.47, 33.51, 34.18, 34.24; located at <http://cmosedu.com/cm0s2/book2.htm>.  
 Dallas Semiconductor, Maxim Application Note 1870, "Demystifying Sigma-Delta ADCs," (Jan. 31, 2003), 15 pgs.  
 Baker, R.J., (2003) *Mixed-Signal Design in the Microelectronics Curriculum*, IEEE University/Government/Industry Microelectronics (UGIM) Symposium, Jun. 30-Jul. 2, 2003.  
 Baker, R.J. (2004) *Delta-Sigma Modulation for Sensing, IEEE/EDS Workshop on Microelectronics and Electron Devices (WMED)*, Apr. 2004.  
 Baker, "CMOS Circuit Design, Layout, and Simulation," Second Edition, IEEE Press, A. John Wiley & Sons, Inc.; Copyright 2005; Chapters 13, 16, 17, 20, 22-24, 28-29; pp. 375-396, 433-522, 613-656, 711-828, 931-1022.  
 Hadrick, M. and Baker, R.J., (2005) *Sensing in CMOS Imagers using Delta-Sigma Modulation*, a general presentation of our work in this area.  
 Baker, R.J. (2005) *Design of High-Speed CMOS Op-Amps for Signal Processing, IEEE/EDS Workshop on Microelectronics and Electron Devices (WMED)*, Apr. 2005.  
 Leslie, M.B., and Baker, R.J., (2006) "Noise-Shaping Sense Amplifier for MRAM Cross-Point Arrays," *IEEE Journal of Solid State Circuits*, vol. 41, No. 3, pp. 699-704.  
 Duvvada, K., Saxena, V., and Baker, R. J., (2006) *High Speed Digital Input Buffer Circuits*, proceedings of the IEEE/EDS Workshop on Microelectronics and Electron Devices (WMED), pp. 11-12, Apr. 2006.

(56)

**References Cited**

OTHER PUBLICATIONS

Saxena, V., Plum, T.J., Jessing, Jr., and Baker, R. J., (2006) *Design and Fabrication of a MEMS Capacitive Chemical Sensor System*, proceedings of the IEEE/EDS Workshop on Microelectronics and Electron Devices (WMED), pp. 17-18, Apr. 2006.

Baker, R.J. and Saxena, V., (2007) *Design of Bandpass Delta Sigma Modulators: Avoiding Common Mistakes*, presented at various universities and companies.

Wikipedia—definition of “Error detection and correction”, pulled from website Jun. 1, 2007, 9 pgs.

Wikipedia—definition of “Hamming code”, pulled from website Jun. 1, 2007, 8 pgs.

Wikipedia—definition of “Linear feedback shift register (LFSR),” pulled from website Jun. 1, 2007, 4 pgs.

Park, “*Motorola Digital Signal Processors—Principles of Sigma-Delta Modulation for Analog-to-Digital Converters*,” Feb. 2010, pp. 1-71.

\* cited by examiner




FIG. 4




FIG. 1




FIG. 2




FIG. 5





FIG. 6






FIG. 7




FIG. 8




FIG. 9




FIG. 10








FIG. 14





FIG. 15






FIG. 16






FIG. 17



**FIG. 19**

**FIG. 18**



**FIG. 23**

**FIG. 20**







FIG. 24

FIG. 27




FIG. 25




FIG. 26




FIG. 29






FIG. 28






FIG. 32

## QUANTIZING CIRCUITS HAVING IMPROVED SENSING

### CROSS-REFERENCE TO RELATED APPLICATION

This application is a continuation of U.S. patent application Ser. No. 15/269,418 which was filed Sep. 19, 2016, now U.S. Pat. No. 10,127,954, which issued on Nov. 13, 2018, which is a continuation U.S. patent application Ser. No. 15/074,759 which was filed on Mar. 18, 2016, now U.S. Pat. No. 9,449,664, which is a continuation of U.S. patent application Ser. No. 14/507,452 which was filed on Oct. 6, 2014, now U.S. Pat. No. 9,299,405, which is a divisional of U.S. patent application Ser. No. 14/076,908, which was filed on Nov. 11, 2013, now U.S. Pat. No. 8,854,899, which is a divisional of U.S. patent application Ser. No. 13/486,535, which was filed on Jun. 1, 2012, now U.S. Pat. No. 8,582,375, which is a divisional of U.S. patent application Ser. No. 12/951,997, which was filed on Nov. 22, 2010, now U.S. Pat. No. 8,194,477, which is a divisional of U.S. patent application Ser. No. 11/820,003, which was filed on Jun. 15, 2007, now U.S. Pat. No. 7,839,703.

### BACKGROUND

#### Field of the Invention

Embodiments of the present invention relate generally to electronic devices and, more specifically, to subtraction circuits and digital-to-analog converters for delta-sigma modulators in electronic devices.

#### Description of the Related Art

Generally, memory devices include an array of memory elements and associated sense amplifiers. The memory elements store data, and the sense amplifiers read the data from the memory elements. To read data, for example, a current is passed through the memory element, and the current or a resulting voltage is measured by the sense amplifier. Conventionally, the sense amplifier measures the current or voltage by comparing it to a reference current or voltage. Depending on whether the current or voltage is greater than the reference, the sense amplifier outputs a value of one or zero. That is, the sense amplifier quantizes or digitizes the analog signal from the memory element into one of two logic states.

Many types of memory elements are capable of assuming more than two states. That is, some memory elements are capable of multi-bit storage. For instance, rather than outputting either a high or low voltage, the memory element may output four or eight different voltage levels, each level corresponding to a different data value. However, conventional sense amplifiers often fail to distinguish accurately between the additional levels because the difference between the levels (e.g., a voltage difference) in a multi-bit memory element is often smaller than the difference between the levels in a single-bit memory element. Thus, conventional sense amplifiers often cannot read multi-bit memory elements reliably. This problem may be increased as high performance multi-bit memory elements become increasingly dense, thereby reducing the size of the memory elements and the difference between the levels (e.g., voltage) to be sensed by the sense amplifiers.

A variety of factors may tend to prevent the sense amplifier from discerning small differences in the levels of a

multi-bit memory element. For instance, noise in the power supply, ground, and reference voltage may cause an inaccurate reading of the memory element. The noise may have a variety of sources, such as temperature variations, parasitic signals, data dependent effects, and manufacturing process variations. This susceptibility to noise often leads a designer to reduce the number of readable states of the memory element, which tends to reduce memory density and increase the cost of memory.

Conventional sense amplifiers present similar problems in imaging devices. In these devices, an array of light sensors output a current or voltage in response to light impinging upon the sensor. The magnitude of the current or voltage typically depends upon the intensity of the light. Thus, the capacity of the sense amplifier to accurately convert the current or voltage into a digital signal may determine, in part, the fidelity of the captured image. Consequently, noise affecting the sense amplifier may diminish the performance of imaging devices.

### BRIEF DESCRIPTION OF THE DRAWINGS

FIG. 1 illustrates an electronic device in accordance with an embodiment of the present invention;

FIG. 2 illustrates a memory device in accordance with an embodiment of the present invention;

FIG. 3 illustrates a memory array in accordance with an embodiment of the present invention;

FIG. 4 illustrates a memory element in accordance with an embodiment of the present invention;

FIG. 5 illustrates I-V traces of memory elements storing different values, in accordance with an embodiment of the present invention;

FIG. 6 illustrates noise in the bit-line current during a read operation;

FIG. 7 illustrates a quantizing circuit in accordance with an embodiment of the present invention;

FIG. 8 illustrates a delta-sigma sensing circuit in accordance with an embodiment of the present invention;

FIGS. 9 and 10 illustrate current flow during operation of the quantizing circuit of FIG. 8;

FIGS. 11-13 illustrate voltages in the quantizing circuit of FIG. 8 when sensing small, medium, and large currents, respectively;

FIG. 14 is a graph of bit-line current versus counter output for the quantizing circuit of FIG. 8;

FIG. 15 is a graph of count versus quantizing circuit output in accordance with an embodiment of the present invention;

FIG. 16 is a block diagram of a delta-sigma modulator in accordance with an embodiment of the present invention;

FIG. 17 is a block diagram of a one-bit delta-sigma modulator in accordance with an embodiment of the present invention;

FIG. 18 illustrates an example of an adder in accordance with an embodiment of the present invention;

FIGS. 19 and 20 each illustrate respective examples of a voltage-to-current converter in accordance with an embodiment of the present invention;

FIGS. 21-22 each illustrate respective examples of the adder illustrated by FIG. 18 in accordance with embodiments of the present invention;

FIG. 23 illustrates a second example of an adder in accordance with an embodiment of the present invention;

FIG. 24 illustrates a third example of a voltage-to-current converter in accordance with an embodiment of the present invention;

FIGS. 25-27 each illustrate respective examples of a current switch in accordance with an embodiment of the present invention;

FIGS. 28-31 each illustrate respective examples of a reference current source in accordance with an embodiment of the present invention; and

FIG. 32 is an example of a system that includes the memory device of FIG. 2 in accordance with an embodiment of the present invention.

#### DETAILED DESCRIPTION OF SPECIFIC EMBODIMENTS

Various embodiments of the present invention are described below. In an effort to provide a concise description of these embodiments, not all features of an actual implementation are described in the specification. It should be appreciated that in the development of any such actual implementation, as in any engineering or design project, numerous implementation-specific decisions must be made to achieve the developers' specific goals, such as compliance with system-related and business-related constraints, which may vary from one implementation to another. Moreover, it should be appreciated that such a development effort might be complex and time consuming but would nevertheless be a routine undertaking of design, fabrication, and manufacture for those of ordinary skill having the benefit of this disclosure.

Some of the subsequently described embodiments may address one or more of the problems with conventional sense amplifiers discussed above. Some embodiments include a quantizing circuit configured to detect small differences in voltages and/or currents. As explained below, the quantizing circuit may sample the measured electrical parameter on multiple occasions and filter, e.g., average or sum, the samples to reduce the impact of noise. As a result, in some embodiments, the quantizing circuit may resolve small differences between voltage or current levels in multi-bit memory elements and/or light sensors, which may allow circuit designers to increase the number of bits stored per memory element and/or the sensitivity of an imaging device.

The following description begins with an overview of examples of systems that employ quantizing circuits in accordance with embodiments of the present invention, and the problems within these systems that may be addressed by the quantizing circuits as described with reference to FIGS. 1-7. Then, specific examples of a quantizing circuit are described with reference to FIGS. 8-15. Next, block diagrams of delta-sigma modulators that may be employed in a quantizing circuit are described with reference to the FIGS. 16 and 17. Finally, circuits for subtracting voltages in a delta-sigma modulator are described with reference to FIGS. 18-25, and circuits for supplying a reference current to a delta-sigma modulator are described with reference to the FIGS. 26-29.

FIG. 1 depicts an electronic device 10 that may be fabricated and configured in accordance with one or more of the present embodiments. The illustrated electronic device 10 includes a memory device 12 that, as explained further below, may include multi-bit memory elements and quantizing circuits. Alternatively, or additionally, the electronic device 10 may include an imaging device 13 having the quantizing circuits.

Myriad devices may embody one or more of the present techniques. For example, the electronic device 10 may be a storage device, a communications device, an entertainment device, an imaging system, or a computer system, such as a

personal computer, a server, a mainframe, a tablet computer, a palm-top computer, or a laptop.

FIG. 2 depicts a block diagram of an embodiment of the memory device 12. The illustrated memory device 12 may include a memory array 14, a quantizing circuit 16, a column decoder 18, a column address latch 20, row drivers 22, a row decoder 24, row address latches 26, and control circuitry 28. As described below with reference to FIG. 3, the memory array 14 may include a matrix of memory elements arranged in rows and columns. As will be appreciated, the imaging device 13 (FIG. 1) may include similar features except that in the case of an imaging device 13, the memory array 14 will include a matrix of imaging elements, such as complementary-metal-oxide semiconductor (CMOS) imaging elements.

When accessing the memory elements, the control circuitry may receive a command to read from or write to a target memory address. The control circuitry 28 may then convert the target address into a row address and a column address. In the illustrated embodiment, the row address bus 30 transmits the row address to the row address latches 26, and a column address bus 32 transmits column address to the column address latches 20. After an appropriate settling time, a row address strobe (RAS) signal 39 (or other controlling clock signal) may be asserted by the control circuitry 28, and the row address latches 26 may latch the transmitted row address. Similarly, the control circuitry 28 may assert a column address strobe 36, and the column address latches 20 may latch the transmitted column address.

Once row and column addresses are latched, the row decoder 24 may determine which row of the memory array 14 corresponds to the latched row address, and the row drivers 22 may assert a signal on the selected row. Similarly, the column decoder 18 may determine which column of the memory array 14 corresponds with the latched column address, and the quantizing circuit 16 may sense a voltage or current on the selected column. Additional details of reading and writing are described below.

FIG. 3 illustrates an example of a memory array 14. The illustrated memory array 14 includes a plurality of bit-lines 38, 40, 42, 44, and 46 (also referred to as BL0-BL4) and a plurality of word-lines 48, 50, 52, 54, 56, 58, 60, and 62 (also referred to as WL0-WL7). These bit-lines and word-lines are electrical conductors. The memory array 14 further includes a plurality of memory elements 64, each of which may be arranged to intersect one of the bit-lines and one of the word-lines. In other embodiments, imaging elements may be disposed at each of these intersections. The memory elements and imaging elements may be referred to generally as internal data storage locations, i.e., devices configured to convey data, either stored or generated by a sensor, when accessed by a sensing circuit, such as the quantizing circuits discussed below. The internal data storage locations may be formed on an integrated semiconductor device that also includes the other components of the memory device 12 (or imaging device 13).

In some embodiments, the illustrated memory elements 64 are flash memory devices. The operation of the flash memory elements is described further below with reference to the FIGS. 4 and 5. It should be noted that, in other embodiments, the memory elements 64 may include other types of volatile or nonvolatile memory. For example, the memory elements 64 may include a resistive memory, such as a phase change memory or magnetoresistive memory. In another example, the memory elements 64 may include a capacitor, such as a stacked or trench capacitor. Some types

of memory elements **64** may include an access device, such as a transistor or a diode associated with each of the memory elements **64**, or the memory elements **64** may not include an access device, for instance in a cross-point array.

FIG. 4 illustrates a circuit **66** that models the operation of an arbitrarily selected memory element **64**, which is disposed at the intersection of WL3 and BL0. This circuit **66** includes a capacitor **68**, a pre-drain resistor **70** ( $R_{PD}$ ), a post-source resistor **72** ( $R_{PS}$ ), and a ground **74**. The resistors **70** and **72** model the other devices in series the memory element **64** being sensed. The illustrated memory element **64** includes a gate **76**, a floating gate **78**, a drain **80**, and a source **82**. In the circuit **66**, the drain **80** and source **82** are disposed in series between the pre-drain resistor **70** and the post-source resistor **72**. The gate **76** is coupled to WL3. The pre-drain resistor **70**, the drain **80**, the source **82**, and the post-source resistor **72** are disposed in series on the bit-line BL0. The capacitor **68**, which models the capacitance of the bit-line, has one plate coupled to ground **74** and another plate coupled to the bit-line BL0, in parallel with the memory elements **64**.

Several of the components of the circuit **66** represent phenomenon affecting the memory elements **64** during operation. The pre-drain resistor **70** generally represents the drain-to-bitline resistance of the memory elements **64** coupled to the bit-line above (i.e., up current from) WL3 when these memory elements **64** are turned on, (e.g., during a read operation). Similarly, the post source resistor **72** generally corresponds to the source-to-ground resistance of the memory elements **64** coupled to the bit-line below WL3 when these memory element **64** is selected. The circuit **66** models electrical phenomena associated with reading the memory elements **64** at the intersection of WL3 and BL0.

The operation of the memory elements **64** will now be briefly described with reference to FIGS. 4 and 5. FIG. 5 illustrates one potential relationship between the bit-line current ( $I_{BIT}$ ), the word-line voltage ( $V_{WL}$ ), and the voltage of the floating gate **78** ( $V_{FG}$ ). As illustrated by FIG. 5,  $V_{FG}$  affects the response of the memory element **64** to a given  $V_{WL}$ . Decreasing the voltage of the floating gate shifts the I-V curve of the memory elements **64** to the right. That is, the relationship between the bit-line current and a word-line voltage depends on the voltage of the floating gate **78**. The memory elements **64** may store and output data by exploiting this effect.

To write data to the memory elements **64**, a charge corresponding to the data may be stored on the floating gate **78**. The charge of the floating gate **78** may be modified by applying voltages to the source **82**, drain **80**, and/or gate **76** such that the resulting electric fields produce phenomenon like Fowler-Northam tunneling and/or hot-electron injection near the floating gate **78**. Initially, the memory elements **64** may be erased by manipulating the word-line voltage to drive electrons off of the floating gate **78**. In some embodiments, an entire column or block of memory elements **64** may be erased generally simultaneously. Once the memory elements **64** are erased, the gate **76** voltage may be manipulated to drive a charge onto the floating gate **78** that is indicative of a data value. After the write operation ends, the stored charge may remain on the floating gate **78** (i.e., the memory elements **64** may store data in a nonvolatile fashion).

As illustrated by FIG. 5, the value stored by the memory element **64** may be read by applying a voltage,  $V_{WL}$ , to the gate **76** and measuring a resulting bit-line current,  $I_{BIT}$ . Each of the I-V traces depicted by FIG. 5 correspond to a different charge stored on the floating gate,  $V_{FG}$ , which should not be

confused with the voltage that is applied to the gate,  $V_{WL}$ . The difference in floating gate **70** voltage,  $V_{FG}$ , between each I-V trace is an arbitrarily selected scaling factor "x." The illustrated I-V traces correspond to eight-different data values stored by the memory element **64**, with a  $V_{FG}$  of 0x representing a binary data value of 000, a  $V_{FG}$  of 1x representing a binary data value of 001, and so on through  $V_{FG}$  of 7x, which represents a binary data value of 111. Thus, by applying a voltage to the gate **76** and measuring the resulting bit-line current, the charge stored on the floating gate **78** may be measured, and the stored data may be read.

The accuracy with which the bit-line current is sensed may affect the amount of data that a designer attempts to store in each memory element **64**. For example, in a system with a low sensitivity, a single bit may be stored on each memory element **64**. In such a system, a floating gate voltage  $V_{FG}$  of 0x may correspond to a value of 0, and a floating gate voltage  $V_{FG}$  of  $-7x$  may correspond to a value of one. Thus, the difference in floating gate voltages  $V_{FG}$  corresponding to different data values may be relatively large, and the resulting differences and bit-line currents for different data values may also be relatively large. As a result, even low-sensitivity sensing circuitry may discern these large differences in bit-line current during a read operation. In contrast, high-sensitivity sensing circuitry may facilitate storing more data in each memory element **64**. For instance, if the sensing circuitry can distinguish between the eight different I-V traces depicted by FIG. 5, then the memory elements **64** may store three bits. That is, each of the eight different charges stored on the floating gate **78** may correspond to a different three-bit value: 000, 001, 010, 011, 100, 101, 110, or 111. Thus, circuitry that precisely measures the bit-line current  $I_{BIT}$  may allow a designer to increase the amount of data stored in each memory element **64**.

However, as mentioned above, a variety of effects may interfere with accurate measurement of the bit-line current. For instance, the position of the memory elements **64** along a bit-line may affect  $R_{PD}$  and  $R_{PS}$ , which may affect the relationship between the word-line voltage  $V_{WL}$  and the bit-line current  $I_{BIT}$ . To illustrate these effects, FIG. 6 depicts noise on the bit-line while reading from the memory element **64**. As illustrated, noise in the bit-line current  $I_{BIT}$  may cause the bit-line current  $I_{BIT}$  to fluctuate. Occasionally, the fluctuation may be large enough to cause the bit-line current  $I_{BIT}$  to reach a level that corresponds with a different stored data value, which could cause the wrong value to be read from the memory elements **64**. For instance, if the bit-line current is sensed at time **84**, corresponding to an arbitrarily selected peak, a data value of 100 may be read rather than the correct data value of 011. Similarly, if the bit-line current is sensed at time **86**, corresponding to an arbitrarily selected local minimum, a data value of 010 may be read rather than a data value of 011. Thus, noise on the bit-line may cause erroneous readings from memory elements **64**.

FIG. 7 depicts a quantizing circuit **16** that may tend to reduce the likelihood of an erroneous reading. The illustrated quantizing circuit **16** includes an analog-to-digital converter **88** and a digital filter **90** coupled to each of the bit-lines **38**, **40**, **42**, **44**, and **46**, respectively. That is, each bit-line **38**, **40**, **42**, **44**, and **46** may connect to a different analog-to-digital converter **88** and digital filter **90**. The digital filters **90**, in turn, may connect to an input/output bus **92**, which may connect to a column decoder **18**, a column address latch **20**, and/or control circuitry **28** (see FIG. 2).

In operation, the quantizing circuit **16** may digitize analog signals from the memory elements **64** in a manner that is relatively robust to noise. As explained below, the quantiz-

ing circuit 16 may do this by converting the analog signals into a bit-stream and digitally filtering high-frequency components from the bit-stream.

The analog-to-digital converter 88 may be a one-bit, analog-to-digital converter or a multi-bit, analog-to-digital converter. In the present embodiment, an analog-to-digital converter 88 receives an analog signal from the memory element 64, e.g., a bit-line current  $I_{BIT}$  or a bit-line voltage  $V_{BL}$ , and outputs a bit-stream that corresponds with the analog signal. The bit-stream may be a one-bit, serial signal with a time-averaged value that generally represents or corresponds to the time-averaged value of the analog signal from the memory element 64. That is, the bit-stream may fluctuate between values of zero and one, but its average value, over a sufficiently large period of time, may be proportional to the average value of the analog signal from the memory element 64. In certain embodiments, the bit-stream from the analog-to-digital converter 88 may be a pulse-density modulated (PDM) version of the analog signal. The analog-to-digital converter 88 may transmit the bit-stream to the digital filter 90 on a bit-stream signal path 94.

The digital filter 90 may remove high-frequency noise from the bit-stream. To this end, the digital filter 90 may be a low-pass filter, such as a counter, configured to average or integrate the bit-stream over a sensing time, i.e., the time period over which the memory element 64 is read. As a result, the digital filter 90 may output a value that is representative of both the average value of the bit-stream and the average value of the analog signal from the memory element 64. In some embodiments, the digital filter 90 is a counter, and the cut-off frequency of the digital filter 90 may be selected by adjusting the duration of the sensing time. In the present embodiment, increasing the sensing time will lower the cutoff frequency. That is, the frequency response of the digital filter 90 may be tuned by adjusting the period of time over which the bit-stream is integrated and/or averaged before outputting a final value. The frequency response of the digital filter 90 is described further below with reference to FIG. 15. For multi-bit memory elements 64, the output from the digital filter 90 may be a multi-bit binary signal, e.g., a digital word that is transmitted serially and/or in parallel.

Advantageously, in certain embodiments, the quantizing circuit 16 may facilitate the use of multi-bit memory elements 64. As described above, in traditional designs, the number of discrete data values that a memory element 64 stores may be limited by sense amps that react to noise. In contrast, the quantizing circuit 16 may be less susceptible to noise, and, as a result, the memory elements 64 may be configured to store additional data. Without the high frequency noise, the intervals between signals representative of different data values may be made smaller, and the number of data values stored by a given memory element 64 may be increased. Thus, beneficially, the quantizing circuit 16 may sense memory elements 64 that store several bits of data, e.g., 2, 3, 4, 5, 6, 7, 8, or more bits per memory element 64.

Although the quantizing circuit 16 may sample the signal from the memory element 64 over a longer period of time than conventional designs, the overall speed of the memory device 12 may be improved. As compared to a conventional device, each read or write operation of the memory device 12 may transfer more bits of data into or out of the memory element 64. As a result, while each read or write operation may take longer, more data may be read or written during the operation, thereby improving overall performance. Further, in some memory devices 12, certain processes may be

performed in parallel with a read or write operation, thereby further reducing the overall impact of the longer sensing time. For example, in some embodiments, the memory array 14 may be divided into banks that operate at least partially independently, so that, while data is being written or read from one bank, another bank can read or write data in parallel.

FIG. 8 illustrates details of one implementation of the quantizing circuit 16. In this embodiment, the digital filter 90 is a counter, and the analog-to-digital converter 88 is a first-order delta-sigma modulator. The illustrated delta-sigma modulator 88 may include a latched comparator 96 (hereinafter the “comparator”), a capacitor 98, and a switch 100. In other embodiments, other types of digital filters and analog-to-digital converters may be employed, such as those described below in reference to FIGS. 17 and 18.

As illustrated, an input of the counter 90 may connect to the bit-stream signal path 94, which may connect to an output of the comparator 96. The output of the comparator 96 may also connect to a gate of the switch 100 by a feedback signal path 102. The output terminal (e.g., source or drain) of the switch 100 may connect in series to one of the bit-lines 38, 40, 42, 44, or 46, and the input terminal of the switch 100 may connect to a reference current source 104 ( $I_{Ref}$ ). One plate of the capacitor 98 may connect to one of the bit-lines 38, 40, 42, 44, or 46, and the other plate of the capacitor 98 may connect to ground.

The illustrated counter 90 counts the number of clock cycles that the bit-stream 94 is at a logic high value or logic low value during the sampling period. The counter may count up or count down, depending on the embodiment. In some embodiments, the counter 90 may do both, counting up one for each clock cycle that the bit-stream has a logic high value and down one for each clock cycle that the bit-stream has a logic low value. Output terminals (D0-D5) of the counter 90 may connect to the input/output bus 92 for transmitting the count. The counter 90 may be configured to be reset to zero or some other value when a reset signal is asserted. In some embodiments, the counter 90 may be a series connection of D-flip flops, e.g., D-flip flops having SRAM or other memory for storing an initial value and/or values to be written to the memory element 64.

In the illustrated embodiment, the clocked comparator 96 compares a reference voltage ( $V_{Ref}$ ) to the voltage of one of the bit-lines 38, 40, 42, 44, or 46 ( $V_{BL}$ ), which may be generally equal to the voltage of one plate of the capacitor 98. The comparator 96 may be clocked (e.g., falling and/or rising edge triggered), and the comparison may be performed at regular intervals based on the clock signal, e.g., once per clock cycle. Additionally, the comparator 96 may latch, i.e., continue to output, values ( $V_{FB}$ ) between comparisons. Thus, when the clock signals the comparator 96 to perform a comparison, if  $V_{BL}$  is less than  $V_{Ref}$  then the comparator 96 may latch its output to a logic low value, as described below in reference to FIG. 9. Conversely, if  $V_{BL}$  is greater than  $V_{Ref}$  then the comparator 96 may latch a logic high value on its output, as described below in reference to FIG. 10. As a result, the illustrated comparator 96 outputs a bit-stream that indicates whether  $V_{BL}$  is larger than  $V_{Ref}$  where the indication is updated once per clock cycle.

Advantageously, in some embodiments, the quantizing circuit 16 may include a single comparator (e.g., not more than one) for each column of multi-level memory elements 64. In contrast, conventional sense amplifiers often include multiple comparators to read from a multi-bit memory cell, thereby potentially increasing device complexity and cost.

The capacitor **98** may be formed by capacitive coupling of the bit-lines **38**, **40**, **42**, **44**, and **46**. In other designs, this type of capacitance is referred to as parasitic capacitance because it often hinders the operation of the device. However, in this embodiment, the capacitor **98** may be used to integrate differences between currents on the bit-lines **38**, **40**, **42**, **44**, or **46** and the reference current to form the bit-stream, as explained further below. In some embodiments, the capacitor **98** may be supplemented or replaced with an integrated capacitor that provides greater capacitance than the “parasitic” bit-line capacitance.

The illustrated switch **100** selectively transmits current  $I_{Ref}$  from the reference current source **104**. In various embodiments, the switch **100** may be a PMOS transistor (as illustrated in FIGS. **8-10**) or an NMOS transistor (as illustrated in FIG. **17**) controlled by the  $V_{FB}$  signal on the feedback signal path **102**.

The operation of the quantizing circuit **16** will now be described with reference to FIGS. **9-12**. Specifically, FIGS. **9** and **10** depict current flows in the quantizing circuit **16** when the comparator **96** is latched low and high, respectively. FIG. **11** illustrates  $V_{BL}$ , the bit-stream output from the comparator **96**, and the corresponding increasing count of the counter **90** for a relatively small bit-line current. FIG. **12** depicts the same voltages when measuring a medium sized bit-line current, and FIG. **13** depicts these voltages when measuring a relatively large bit-line current.

To measure the current through the memory element **64**, the illustrated delta-sigma modulator **88** exploits transient effects to generate a bit-stream representative of the bit-line current  $I_{BIT}$ . Specifically, the delta-sigma modulator **88** may repeatedly charge and discharge the capacitor **98** with a current divider that subtracts the bit-line current  $I_{BIT}$  from the reference current  $I_{REF}$ . Consequently, a large current through the memory element **64** may rapidly discharge the capacitor **98**, and a small current through the memory element **64** may slowly discharge the capacitor **98**.

To charge and discharge the capacitor **98**, the delta-sigma modulator **88** switches between two states: the state depicted by FIG. **9** (hereinafter “the charging state”) and the state depicted by FIG. **10** (hereinafter “the discharging state”). Each time the delta-sigma modulator **88** changes between these states, the bit-stream changes from a logic high value to a logic low value or vice versa. The proportion of time that the delta-sigma modulator **88** is in the state illustrated by either FIG. **9** or FIG. **10** may be proportional to the size of the bit-line current  $I_{BIT}$  through the memory element **64**. The larger the bit-line current  $I_{BIT}$ , the more time that the delta-sigma modulator **88** is in the state illustrated by FIG. **9**, rather than the state illustrated by FIG. **10**, and the more time that the bit-stream has a logic low value.

Starting with the charging state (FIG. **9**), the capacitor **98** may initially accumulate a charge. To this end, the output of the comparator **96** is latched to logic low, which, as mentioned above, may occur when  $V_{BL}$  is less than  $V_{Ref}$ . The logic low may be conveyed to switch **100** by the feedback signal path **102**, and the switch **100** may close, thereby conducting the reference current  $I_{Ref}$  through one of the bit-lines **38**, **40**, **42**, **44**, or **46**, as indicated by the larger arrows in FIG. **9**. A portion of the electrons flowing through the reference current source **104** may be stored by the capacitor **98**, as indicated by the smaller-horizontal arrows, and the remainder may be conducted through the memory element **64**, i.e., the bit-line current  $I_{BIT}$ , as indicated by the smaller vertical arrows. Thus, the capacitor **98** may accumulate a charge, and  $V_{BL}$  may increase.

The comparator **96** and the reference current source **104** may cooperate to charge the capacitor **98** for a discrete number of clock cycles. That is, when the delta-sigma modulator **88** enters the charging state, the delta-sigma modulator **88** may remain in this state for an integer number of clock cycles. In the illustrated embodiment, the comparator **96**, the output of which is latched, changes state no more than once per clock cycle, so the switch **100**, which is controlled by the output of the comparator **96**,  $V_{FB}$ , conducts current for a discrete number of clock cycles. As a result, the reference current source **104** conducts current  $I_{Ref}$  through the bit-line and into the capacitor **98** for an integer number of clock cycles.

After each clock cycle of charging the capacitor **98**, the delta-sigma modulator **88** may transition from the charging state to the discharging state, which is illustrated by FIG. **10**, depending on the relative values of  $V_{BL}$  and  $V_{Ref}$ . Once per clock cycle (or at some other appropriate interval, such as twice per clock cycle), the comparator **96** may compare the voltage of the capacitor  $V_{BL}$  to the reference voltage  $V_{Ref}$ . If the capacitor **98** has been charged to the point that  $V_{BL}$  is greater than  $V_{Ref}$ , then the output of the comparator **96** may transition to logic high, as illustrated in FIG. **10**. The logic high signal may be conveyed to the switch **100** by the feedback signal path **102**, thereby opening the switch **100**. As a result, the reference current source **104** may cease flowing current through the memory element **64** and into the capacitor **98**, and the capacitor **98** may begin to discharge through the memory element **64**.

In the present embodiment, the delta-sigma modulator **88** discharges the capacitor **98** for a discrete number of clock intervals. After each clock cycle of discharging the capacitor **98**, the delta-sigma modulator **88** compares  $V_{BL}$  to  $V_{Ref}$ . If  $V_{BL}$  is still greater than  $V_{Ref}$ , then the comparator **96** may continue to output a logic high signal, i.e.,  $V_{FB}=1$ , and the switch **100** remains open. On the other hand, if enough current has flowed out of the capacitor **98** that  $V_{BL}$  is less than  $V_{Ref}$ , then the comparator **96** may output a logic low signal, i.e.,  $V_{FB}=0$ , and the switch **100** may close, thereby transitioning the delta-sigma modulator **88** back to the charging state and initiating a new cycle.

The counter **90** may count the number of clock cycles that the delta-sigma modulator **88** is in either the charging state or the discharging state by monitoring the bit-stream signal path **94**. The bit-stream signal path **94** may transition back and forth between logic high and logic low with the output of the comparator **96**,  $V_{FB}$ , and the counter **90** may increment and/or decrement a count once per clock cycle (or other appropriate interval) based on whether the bit-stream is logic high or logic low. After the sensing time has passed, the counter **90** may output a signal indicative of the count on output terminals **D0-D5**. As explained below, the count may correspond, e.g., proportionally, to the bit-line current,  $I_{BIT}$ .

FIGS. **11-13** illustrate voltages  $V_{FB}$  and  $V_{BL}$  in the quantizing circuit **16** when reading a memory element **64**. Specifically, FIG. **11** illustrates a low-current case, in which the value stored by the memory element **64** corresponds to a relatively low bit-line current. Similarly, FIG. **12** illustrates a medium-current case, and FIG. **13** illustrates a high-current case. In each of these figures, the ordinate of the lower trace represents the voltage of the bit-stream signal path **94**,  $V_{FB}$ , and the ordinate of the upper trace illustrates the bit-line voltage,  $V_{BL}$ . The abscissa in each of the traces represents time, with the lower trace synchronized with the upper trace, and the duration of the time axes is one sensing time **106**.

## 11

As illustrated by FIG. 11, the counter 90 is initially set to zero (or some other appropriate value) by asserting a reset signal. In some embodiments, the delta-sigma modulator 88 may undergo a number of start-up cycles to reach steady-state operation before initiating the sensing time and resetting the counter 90. At the beginning of the illustrated read operation, the delta-sigma modulator 88 is in the charging state, which charges the capacitor 98 and increases  $V_{BL}$ , as indicated by dimension arrow 108. At the beginning of the next clock cycle, the comparator 96 compares the bit-line voltage to the reference voltage and determines that the bit-line voltage is greater than the reference voltage. As a result, the bit-stream signal path 94 ( $V_{FB}$ ) transitions to a logic high voltage, and the delta-sigma modulator 88 transitions to the discharging state. Additionally, the counter 90 increments the count by one to account for one clock cycle of the bit-stream signal 94 holding a logic low value. Next, the charge stored on the capacitor 98 drains out through the memory element 64, and the bit-line voltage drops until the comparator 96 detects that  $V_{BL}$  is less than  $V_{Ref}$ , at which point the cycle repeats. The cycle has a period 112, which may be divided into a charging portion 114 and a discharging portion 116. Once during each cycle in the sensing time 106, the count stored in the counter 90 may increase by one. At the end of the sensing time 106, the counter 90 may output the total count.

A comparison of FIG. 11 to FIGS. 12 and 13 illustrates why the count correlates with the bit-line current. In FIG. 13, the high-current case, the stored charge drains from the capacitor 98 quickly, relative to the other cases, because the bit-line current  $I_{BIT}$  is large and, as a result, the delta-sigma modulator 88 spends more time in the charging state than the discharging state. As a result, the bit-stream has a logic low value for a large portion of the sensing time 106, thereby increasing the count.

The capacitance of the capacitor 98 may be selected with both the clock frequency and the range of expected bit-line currents in mind. For example, the capacitor 98 may be large enough that the capacitor 98 does not fully discharge or saturate when the bit-line current  $I_{BIT}$  is either at its lowest expected value or at its highest expected value. That is, in some embodiments, the capacitor 98 generally remains in a transient state while reading the memory element 64. Similarly, the frequency at which the comparator 96 is clocked may affect the design of the capacitor 98. A relatively high frequency clock signal may leave the capacitor 98 with relatively little time to discharge or saturate between clock cycles, thereby leading a designer to choose a smaller capacitor 98.

Similarly, the size of the reference current may be selected with the range of expected bit-line currents in mind. Specifically, in certain embodiments, the reference current is less than the largest expected bit-line current  $I_{BIT}$ , so that, in the case of maximum bit-line current  $I_{BIT}$ , the capacitor 98 can draw charge from the reference current while the rest of the reference current flows through the memory element 64.

FIG. 14 illustrates the relationship between the bit-line current  $I_{BIT}$  and the count for the presently discussed embodiment. As illustrated by FIG. 14, the count is generally proportional to the bit-line current  $I_{BIT}$ . This relationship is described by the following equation (Equation 1), in which  $N_{ST}$  represents the number of clock cycles during the sensing time:

$$I_{Bit}/I_{Ref} = \text{Count}/N_{ST}$$

## 12

Thus, in the illustrated embodiment, the count is indicative of the bit-line current  $I_{BIT}$ , which is indicative of the value stored by the memory element 64.

Advantageously, the quantizing circuit 16 may categorize the bit-line current  $I_{BIT}$  as falling into one of a large number of categories, each of which is represented by an increment of the count. That is, the quantizing circuit 16 may resolve small differences in the bit-line current  $I_{BIT}$ . The resolution of the quantizing circuit 16 may be characterized by the following equation (Equation 2), in which  $I_{MR}$  represents the smallest resolvable difference in bit-line current  $I_{BIT}$ , i.e., the resolution of the quantizing circuit 16:

$$I_{MR} = I_{Ref} N_{ST}$$

Thus, the resolution of the quantizing circuit 16 may be increased by increasing the sensing time or the clock frequency or by decreasing  $I_{Ref}$ , which may limit the maximum cell current since  $I_{MR}$  is less than  $I_{Ref}$ .

The resolution of the quantizing circuit 16 may facilitate storing multiple bits in the memory element 64 or detecting multiple levels of light intensity in an image sensor element. For example, if the quantizing circuit 16 is configured to categorize the bit-line current  $I_{BIT}$  into one of four different levels, then the memory element 64 may store two-bits of data or, if the quantizing circuit 16 is configured to categorize the bit-line current  $I_{BIT}$  into one of eight different current levels, then the memory element 64 may store three-bits of data. For the present embodiment, the number of bits stored by the memory element 64 may be characterized by the following equation (Equation 3), in which  $N_B$  represents the number of bits stored by a memory element 64 and  $I_{Range}$  represents the range of programmable bit-line currents through the memory element 64:

$$N_B = \log(I_{Range}/I_{MR})/\log 2$$

In short, in the present embodiment, greater resolution translates into higher density data storage for a given memory element 64.

FIG. 15 is a graph that illustrates one way in which the counter 90 may be configured to further reduce the effects of noise. In FIG. 15, the abscissa represents the count, and the ordinate represents the output of the quantizing circuit 16. In the present embodiment, the three-least-significant digits of the count are disregarded as potentially corrupted by noise. That is, D0-D2 (FIG. 8) either do not connect to the input/output bus 92 or are not interpreted as conveying data that is stored by the memory element 64. As a result, a range of counter values may represent a single data value stored by the memory element 64. For example, in the present embodiment, count values ranging from 00 1000 to 00 1111 are construed as representing a data value of 001. Representing data in this manner may further reduce the effects of noise because, even if noise affects the count, in many embodiments, it would have to affect the count in a consistent manner over a substantial portion of the sensing time to affect the more significant digits of the count. That is, disregarding less significant digits may lower the cutoff frequency of the counter 90. In other embodiments, fewer, more, or no digits may be truncated from the count as potentially representing noise.

Truncating less significant digits may introduce a rounding error, or a downward bias, in the output. This effect may be mitigated by presetting the counter 90 in a manner that accounts for this bias. The counter 90 may be present either before reading from the memory element 64 or before writing to the memory element 64. In some embodiments, the preset value may be one-half of the size of the range of

13

counter values that represent a single output value. In other words, if  $m$  digits are truncated from the output, then the counter **90** may be preset to one-half of  $2^m$  before reading from a memory element **64** or before writing to the memory element **64**. In some embodiments, the memory **91** may store this preset value.

Delta-sigma modulators may be formed with a variety of circuit topologies. A broad array of these topologies is illustrated by FIG. **16**, which is a block diagram of an example of a first-order delta-sigma modulator **120**. As described below, the embodiment of FIG. **16** is generic to the delta-sigma modulator **88** illustrated in FIG. **8**. The illustrated delta-sigma modulator **120** includes an adder **122**, an integrator **124**, an analog-to-digital converter (A/D) **126**, and a digital-to-analog converter (D/A) **128**. The illustrated adder **122** receives an analog input signal **130** and a feedback signal **132** from the digital-to-analog converter **128**. The illustrated adder **122** outputs a delta signal **134** to an input of the integrator **124**, which outputs a sigma signal **136** to an input of the analog-to-digital converter **126**. The analog-to-digital converter **126** also receives a reference signal **138**. The analog-to-digital converter **126** outputs a digital output signal **140**, which is received by an input to the digital-to-analog converter **128**.

FIG. **17** is a block diagram of an example of a one-bit delta-sigma modulator **142**, which is an embodiment of the delta-sigma modulator **120** illustrated by FIG. **16**, and which is generic to the delta-sigma modulator **88** illustrated by FIG. **8**. In this example, the integrator **124** is a capacitor and the analog-to-digital converter **126** is a comparator. The reference signal **138** is a voltage  $V_{REF}$ , and the digital-to-analog converter **128** includes a switch **144** and a reference current source **146**.

In operation, the illustrated delta-sigma modulator **142** measures the analog input signal **130** by integrating a difference between the analog input signal and the feedback signal **132** and exercising feedback control over this integrated difference. The greater the difference, the stronger or the more frequent the feedback signal **132**. The analog signals may be voltage signal or current signals. Examples that integrate a difference in analog voltage signals are described below. Previously, an example of an analog current signal was described in reference to FIG. **8**. In this embodiment, the difference between the bit-line current  $I_{Bit}$  and the reference current  $I_{Ref}$  is integrated by the voltage of the capacitor **98**, and the comparator **96** controls this voltage by outputting feedback on the feedback signal path **102**. In certain embodiments, if the strength of the feedback signal is held relatively constant when it is applied, the proportion of time that the feedback signal is applied is indicative of the analog input signal **130**. Thus, consistently applying a feedback signal of the same strength may improve the correlation between the digital output **140** and the analog input **130**, thereby potentially improving the accuracy of the quantizing circuit **16**.

The following figures illustrate embodiments of the adder **122** and the digital-to-analog converter **128** that may apply the feedback signal **132** in a relatively consistent manner. FIGS. **18-22** illustrate adders configured to add the analog input signal **130** and the feedback signal **132** (or its inverse), where the analog input signal **130** and/or the feedback signal **132** is a voltage, and FIGS. **23-29** illustrate examples of the digital-to-analog converter **128**. Some of the following embodiments are believed to improve the precision of the delta-sigma modulators **120** and/or **142** and/or lower the power consumption of these components relative to conventional designs, as described below.

14

FIG. **18** illustrates a first embodiment of the adder **122** of FIGS. **16** and **17**. This embodiment is designated with reference number **148**. The illustrated adder **148** includes voltage-to-current converters **150** and **152**. In the present embodiment, the input terminal of the voltage-to-current converter **150** is connected to an analog input signal  $V_{IN-Analog}$ , and the input terminal of the voltage-to-current converter **152** is connected to a voltage feedback signal  $V_{Feedback}$ . Details of examples of voltage-to-current converters are described below with reference to the FIGS. **19** and **20**. In operation, the voltage-to-current converter **150** may convert  $V_{IN-Analog}$  to a current  $I_m$ , and the voltage-to-current converter **152** may convert  $V_{Feedback}$  to a current  $I_f$ . The output terminals of the voltage-to-current converters **150** and **152** may be coupled to one another and an adder output  $I_m+I_f$ . Thus, the adder **148** may be configured to convert voltage signals to currents and combine those currents.

In other embodiments, the adder **148** may convert only one voltage signal to a current and combine that current with another signal that is already in the form of a current. Also, in some embodiments, the current outputs from the voltage-to-current converters  $I_m$  and  $I_f$  may have different signs, and the adder **148** may output a difference of these currents, i.e., the adder **148** may also subtract.

FIG. **19** illustrates an example of a voltage-to-current converter **154**, which may embody one or both of the voltage-to-current converters **150** and **152** illustrated in FIG. **18**. In this example, the voltage-to-current converter **154** includes an NMOS transistor **156** and a resistor **158**. The resistor **158** may be disposed in series between ground **74** and the source of the transistor **156**, and an input voltage  $V_{IN}$ , such as  $V_{IN-Analog}$  or  $V_{feedback}$  in FIG. **18**, may connect to the gate of the transistor **156**. In the present embodiment, the transistor **156** has a gate width sized such that a voltage difference between the gate and the source  $V_{GS}$  is near the threshold voltage of the transistor  $V_{THN}$ . Consequently, in certain embodiments, the transistor **156** operates in the linear region of its I-V curve. As a result, in some embodiments, the operation of the voltage-to-current converter **154** may be characterized by the following equation (Equation 4), in which  $I$  corresponds to the output current signal and  $R$  corresponds to the resistance of the resistor **158**:

$$I=(V_{IN}-V_{THN})/R$$

FIG. **20** illustrates another example of a voltage-to-current converter **160**, which may embody one or both of the voltage-to-current converters **150** and **152** illustrated in FIG. **18**. The voltage-to-current converter **160** may include a PMOS transistor **162** (in contrast to the NMOS transistor of the previous embodiment) and a resistor **164**, which may be disposed in series between the transistor **162** and a voltage source  $V_{DD}$ . The transistor **162** may have a relatively wide gate that is sized such that its operation may be described by the following equation (Equation 5), wherein  $V_{THP}$  is the threshold voltage of the transistor **162**,  $I$  is the output current signal, and  $R$  is the resistance of the resistor **164**:

$$I=(V_{DD}-V_{THP}-V_{IN})/R$$

FIGS. **21** and **22** illustrate examples of the adder **148** (FIG. **18**) that may employ the voltage-to-current converters **154** and **160** (FIGS. **19** and **20**). In FIG. **21**, the adder **151** sources the current  $I_m+I_f$ . The adder **151** may include two voltage-to-current converters **153** and **155**, which may correspond to the voltage-to-current converter **154** of FIG. **19**, and two current mirrors **157** and **159**. In FIG. **22**, the adder **161** sinks the current  $I_m+I_f$ . The adder **161** may include

voltage-to-current converters **163** and **165**, which may correspond to the voltage-to-current converter **160** of FIG. **20**, and two current mirrors **167** and **169**.

FIG. **23** illustrates another example of an adder **166**, which may embody the adder **122** illustrated in FIGS. **16** and **17**. In this embodiment, the adder **166** includes a pair of voltage-to-current converters **168** and **170** that are configured to convert a voltage signal into a current signal that may span two directions of current flow. That is, the output of the voltage-to-current converters  $\pm I_{IN}$  and  $\pm I_f$  may flow in both directions, depending on the input voltage signal  $\pm V_{IN}$  or  $\pm V_f$ . Consequently, the output  $\pm I_{IN} \pm I_f$  may also range over two directions of current flow.

FIG. **24** illustrates a voltage-to-current converter **172**, which may embody one or both of the voltage-to-current converters **168** and **170** illustrated in FIG. **23**. The present voltage-to-current converter **172** may include a forward-current converter **174** and a reverse-current converter **176**.

The forward-current converter **174** may include two-PMOS transistors **178** and **180**, an NMOS transistor **182**, and a resistor **184**. The resistor **184** may be disposed in series between the transistor **182** and ground **74**. The transistor **178** may be disposed in series between the voltage source  $V_{DD}$  and the transistor **182**. The transistors **178** and **180** may share a gate signal **188**, which may be coupled to a node in series between the transistors **178** and **182**. The transistor **180** may be disposed in series between the voltage source  $V_{DD}$  and an output signal path **190**, which carries an output current signal  $\pm I$ . The gate of the transistor **182** may be connected to an input signal path **192**, which carries an input voltage signal  $\pm V_{IN}$ . The transistors **178**, **180**, and **182** may have relatively wide gate widths, so that, during normal operation, they operate in the linear region of their I-V curves.

Similarly, the reverse-current converter **176** may include two-NMOS transistors **194** and **196**, a PMOS transistor **198**, and a resistor **200**. The resistor **200** may be disposed in series between the voltage source  $V_{DD}$  and the transistor **198**. The transistor **194** may be disposed in series between ground **74** and the transistor **198**. The transistors **194** and **196** may share a gate signal **202**, which may be coupled to a node in series between the transistors **198** and **194**. The transistor **196** may be disposed in series between ground **74** and the output signal path **190**. The gate of transistor **198** may be connected to the input signal path **192**. The transistors **198**, **194**, and **196** may have relatively wide gate widths, so that, during normal operation, they operate in the linear region of their I-V curves.

In operation, either the forward-current converter **174** may act as a current source or the reverse-current converter **176** may act as a current sink, depending on the input voltage signal  $\pm V_{IN}$ . If the input voltage signal  $\pm V_{IN}$  is positive, then the transistor **198** may turn off, and the transistor **182** may turn on. As a result, in some embodiments, a current  $I_1$  may flow through the transistor **182**, and a current  $I_2$  may cease flowing through transistor **198**. Because the transistors operate in the linear region of their I-V curve, the magnitude of the currents  $I_1$  and  $I_2$  may be generally proportional to the magnitude of the input voltage signal  $\pm V_{IN}$ . The transistors **178** and **180** may mirror the current  $I_1$  on the output signal path **190**, and the transistors **194** and **196** may mirror the current  $I_2$  on the output signal path **190**.

Advantageously, the current mirrors formed by the transistors **178**, **180**, **194**, and **196** may form the output current  $\pm I$  in a manner that is relatively robust to loads applied to the output signal path **190**. As a result, the adder **122** (FIGS. **16** and **17**) may receive signals that accurately convey infor-

mation about the analog input or the state of the delta-sigma modulation circuit **120** or **142**, such as the magnitude of an input voltage or a feedback voltage. This is believed to improve the accuracy of the adder.

FIG. **25** illustrates an example of a switch **204**, which may be employed in place of the current switch **100** in the delta-sigma modulation circuit **88** illustrated by FIG. **8**. The illustrated switch **204** routes the reference current  $I_{Ref}$  either to ground **74** or to a bit-line **208** based on the feedback signal  $V_{feedback}$  from the comparator **96** (FIG. **8**) on the feedback signal path **102**. In certain embodiments, the switch **204** converts a digital signal from the analog-to-digital converter **126**, i.e., a digital feedback signal, to an analog signal, i.e., the reference current. The switch **204** may include two PMOS transistors **210** and **212**, the gates of which may be controlled by  $V_{feedback}$  or its complement.

Advantageously, the switch **204** may supply a relatively uniform reference current  $I_{Ref}$  because of the reference current  $I_{Ref}$  flows generally constantly, rather than turning on and off. As a result, transient effects, such as parasitic induction and capacitance, that may distort the reference current  $I_{Ref}$  in other designs may be avoided. This is believed to improve the accuracy of the delta-sigma modulator **88** (FIG. **8**) because the bit-line current  $I_{Bit}$  is measured against, e.g., subtracted from, a relatively constant quantity.

FIG. **26** illustrates another example of a switch **214**, which may be employed in place of the current switch **100** in the delta-sigma modulation circuit **88** illustrated by FIG. **8**. The switch **214** may include PMOS transistors **216** and **218** and a capacitor **220**. In the present embodiment, one plate of the capacitor **220** is coupled to ground **74** and the other plate is coupled to both the reference voltage  $V_{Ref}$  (which is also coupled to the comparator **96** in FIG. **8**) and one terminal of the transistor **216**. The other terminal of the transistor **216** may be connected to the reference current source **104** along with one terminal of the transistor **218**. The gates of the transistors **216** and **218** may be connected to the feedback signal path **102** to receive  $V_{feedback}$ .

In operation, the capacitor **220** may supplement the reference current source **104** during transient periods with an elevated load. When the transistors **216** and **218** turn on, and the reference current  $I_{Ref}$  begins to flow through the bit-line **208**, the reference current source **104** may be unable to supply a uniform current due to parasitic, transient effects. To counteract these transient effects, the reference voltage may maintain a charge on the capacitor **220**, which may supply current to the bit-line **208** and the current from the reference current source **104**. In other words, the capacitor **220** may store and release energy to average out the load seen by the reference current source **104**. As a result, the reference current  $I_{Ref}$  may be more uniform, which is believed to improve the accuracy of the delta-sigma modulation circuit **88** (FIG. **8**). In certain embodiments, the switch **214** converts a digital signal from the analog-to-digital converter **126** to an analog signal.

FIG. **27** illustrates another example of a switch **223**, which may be employed in place of the current switch **100** in the delta-sigma modulation circuit **88** illustrated by FIG. **8**. The illustrated switch **223** includes a PMOS transistor **224** and a capacitor **225**. One terminal of the transistor **224** may be connected to one plate of the capacitor **225** and the reference current source **104**. The other terminal of the transistor **224** may be connected to the bit-line **208**, and the gate of the transistor **224** may be connected to the feedback signal path **102** to receive  $V_{feedback}$  from the comparator **96** (FIG. **8**). One plate of the capacitor **225** may also be connected to ground.

In operation, the capacitor **225** may deliver supplemental power to the reference current source **104**. When the transistor **224** turns on or off, the load on the reference current source **104** may spike, thereby potentially disrupting the reference current  $I_{Ref}$ . To counteract this effect, the capacitor **225** may store charge from the reference current  $I_{Ref}$  when the transistor **224** is turned off, and a release that charge through the bit-line **208** when the transistor **224** turns on. In certain embodiments, the switch **223** converts a digital signal from the analog-to-digital converter **126** to an analog signal. Advantageously, the switch **223** may provide a relatively stable reference current  $I_{Ref}$ . Additionally, in the present embodiment, the switch **223** consumes relatively little power because the reference current  $I_{Ref}$  does not flow to ground **74** when it is not flowing through the bit-line **208**.

FIG. **28** illustrates an example of a reference current source **227**, which may embody the reference current source **104** illustrated in the embodiments of FIGS. **8-10** and **23-24**. As described below, the reference current source **227** may cooperate with the switch **100** to convert a digital signal from the analog-to-digital converter **126** to an analog signal. The illustrated reference current source **227** includes a reference device **228** and a current mirror **229** with PMOS transistors **230** and **232**. The reference device **228** may include a reference resistor, a reference memory element, or any other device configured to conduct a relatively uniform current. The reference device **228** may be disposed in series between ground **74** and a terminal of the transistor **230**. The other terminal of the transistor **230** may be connected to the voltage source  $V_{DD}$ . The gates of the transistors **230** and **232** may be connected to one another and to a node disposed in series between the transistors **230** and the reference device **228**. The terminals of the transistor **232** may be connected to the voltage source  $V_{DD}$  and an output signal path **236** through which the reference current  $I_{Ref}$  flows.

In operation, the current mirror **229** may copy the current flowing through the reference device **228** to the output signal path **236**. The current mirror **229** may do this while keeping the reference current  $I_{Ref}$  relatively constant regardless of heavy loads from the bit-line, e.g., immediately after the current switch **100** turns on (FIG. **8**). Advantageously, this is believed to improve the accuracy of the delta-sigma modulation circuit **88** (FIG. **8**) relative to conventional designs.

FIG. **29** illustrates another example of a reference current source **238**, which may embody the reference current source **104** illustrated in the embodiments of FIGS. **8-10** and **23-24**. As described below, the reference current source **238** may cooperate with the switch **100** to convert a digital signal from the analog-to-digital converter **126** to an analog signal. The illustrated reference current source **238** includes the features of the reference current source **224** illustrated in FIG. **27**. However, the reference current source **238** may also include additional components to form a cascade current mirror **240**. The illustrated cascade current mirror **240** includes the current mirror **228** and a second current mirror **242**. The second current mirror **242** may include PMOS transistors **244** and **246**. Advantageously, in systems employing the cascade current mirror **240** the reference current  $I_{Ref}$  may track the current through the reference device **226** more accurately than systems employing a single current mirror.

FIG. **30** illustrates another example of a reference current source **248**, which may embody the reference current source **104** illustrated in the embodiments of FIGS. **8-10** and **23-24**. As described below, the reference current source **248** may cooperate with the switch **100** to convert a digital signal from the analog-to-digital converter **126** to an analog signal.

The illustrated reference current source **248** includes a resistor **250** and the switch **204**, which was previously described with reference to FIG. **25**. The resistor **250** may be disposed in series between the voltage source  $V_{DD}$  and the switch **204**.

In operation, the reference current source **248** may output a reference current  $I_{Ref}$  that is generally proportional to the voltage between the voltage source  $V_{DD}$  and the voltage of the bit-line  $V_{BL}$ . In certain embodiments, the feedback signal  $V_{feedback}$  from the comparator **96** (FIG. **8**) keeps the voltage of the bit-line  $V_{BL}$  approximately equal to the reference voltage  $V_{Ref}$ . Although the voltage of the bit-line  $V_{BL}$  fluctuates relative to the reference voltage  $V_{Ref}$  (as illustrated by **11-13**), this fluctuation may be relatively small as a percentage of the reference voltage  $V_{Ref}$ . As a result, for certain purposes, the voltage of the bit-line  $V_{BL}$  may be considered approximately equal to the reference voltage  $V_{Ref}$ . Consequently, in the present embodiment, the reference current may be described by the following equation (Equation 6), in which  $R$  is the resistance of the resistor **250**:

$$I_{Ref} = (V_{DD} - V_{Ref}) / R$$

FIG. **31** illustrates another example of a reference current source **252**, which may embody the reference current source **104** illustrated in the embodiments of FIGS. **8-10** and **25-26**. As described below, the reference current source **252** may cooperate with the switch **100** to convert a digital feedback signal from the analog-to-digital converter **126** to an analog signal. In the present embodiment, the reference current source **252** includes two PMOS transistors **254** and **256** and a capacitor **258**. One plate of the illustrated capacitor **258** is connected to a terminal of each of the transistors **254** and **256**, and the other plate of the capacitor **258** is connected to ground **74**. The other terminal of the transistor **254** is connected to voltage source  $V_{DD}$ , and the other terminal of the transistor **256** is connected to a reference current signal path **260**, which carries the reference current  $I_{Ref}$ . The gates of the transistors **254** and **256** may be connected to complementary clock signals. As a result, in the present embodiment, the transistors **254** and **256** are neither both on at the same time nor both off at the same time.

In operation, the capacitor **258** may output charge at a generally repeatable rate. In the present embodiment, the capacitor **258** is charged by a current from the voltage source  $V_{DD}$  when the clock signal is logic high. When the clock signal transitions to logic low, the capacitor **258** discharges through the transistor **256**. In this embodiment, assuming that  $V_{Ref}$  approximates  $V_{BL}$ , the operation of the reference current source **252** may be described by the following equation (Equation 7), in which  $C_4$  represents the capacitance of the capacitor **258** and  $I_{Avg}$  represents the average reference current  $I_{Ref}$ :

$$I_{Avg} = C_4 * (V_{DD} - V_{Ref})$$

Advantageously, the reference current source **252** may deliver a uniform reference current, on average, while consuming relatively little power. As indicated by Equation 7, in certain embodiments, the average reference current  $I_{Avg}$  is a function of generally constant parameters,  $C_4$ ,  $V_{DD}$ , and  $V_{Ref}$ . As a result, the average reference current  $I_{Avg}$  may be generally the same when reading from, and writing to, the memory element **64**. In certain embodiments, this increases the likelihood that the value read from the memory element **64** accurately reflects the value written to the memory element **64**. Further, because the capacitor **258** conserves

charge and generates relatively little heat compared to a resistor, the reference current source **252** may consume less power than other designs.

FIG. **32** depicts an exemplary processor-based system **310** that includes the memory device **12**. Alternatively or additionally, the system **310** may include the imaging device **13**. The system **310** may be any of a variety of types such as a computer, pager, cellular phone, personal organizer, control circuit, etc. In a typical processor-based system, one or more processors **312**, such as a microprocessor, control the processing of system functions and requests in the system **310**. The processor **312** and other subcomponents of the system **310** may include quantizing circuits, such as those discussed above.

The system **310** typically includes a power supply **314**. For instance, if the system **310** is a portable system, the power supply **314** may advantageously include a fuel cell, permanent batteries, replaceable batteries, and/or rechargeable batteries. The power supply **314** may also include an AC adapter, so the system **310** may be plugged into a wall outlet, for instance. The power supply **314** may also include a DC adapter such that the system **310** may be plugged into a vehicle cigarette lighter, for instance.

Various other devices may be coupled to the processor **312** depending on the functions that the system **310** performs. For instance, a user interface **316** may be coupled to the processor **312**. The user interface **316** may include buttons, switches, a keyboard, a light pen, a mouse, a digitizer and stylus, and/or a voice recognition system, for instance. A display **318** may also be coupled to the processor **312**. The display **318** may include an LCD, an SED display, a CRT display, a DLP display, a plasma display, an OLED display, LEDs, and/or an audio display, for example. Furthermore, an RF sub-system/baseband processor **320** may also be coupled to the processor **312**. The RF sub-system/baseband processor **320** may include an antenna that is coupled to an RF receiver and to an RF transmitter (not shown). One or more communication ports **322** may also be coupled to the processor **312**. The communication port **322** may be adapted to be coupled to one or more peripheral devices **324** such as a modem, a printer, a computer, or to a network, such as a local area network, remote area network, intranet, or the Internet, for instance.

The processor **312** generally controls the system **310** by implementing software programs stored in the memory. The memory is operably coupled to the processor **312** to store and facilitate execution of various programs. For instance, the processor **312** may be coupled to the volatile memory **326** which may include Dynamic Random Access Memory (DRAM) and/or Static Random Access Memory (SRAM). The volatile memory **326** is typically large so that it can store dynamically loaded applications and data. As described further below, the volatile memory **326** may be configured in accordance with embodiments of the present invention.

The processor **312** may also be coupled to the memory device **12**. The memory device **12** may include a read-only memory (ROM), such as an EPROM, and/or flash memory to be used in conjunction with the volatile memory **326**. The size of the ROM is typically selected to be just large enough to store any necessary operating system, application programs, and fixed data. Additionally, the non-volatile memory **328** may include a high capacity memory such as a tape or disk drive memory.

The memory device **10** and volatile memory **326** may store various types of software, such as an operating system or office productivity suite including a word processing

application, a spreadsheet application, an email application, and/or a database application.

While the invention may be susceptible to various modifications and alternative forms, specific embodiments have been shown by way of example in the drawings and have been described in detail herein. However, it should be understood that the invention is not intended to be limited to the particular forms disclosed. Rather, the invention is to cover all modifications, equivalents, and alternatives falling within the spirit and scope of the invention as defined by the following appended claims.

What is claimed is:

**1.** A device, comprising:

an imaging element configured to output a first signal in response to light impinging upon the imaging element; and

a quantizing circuit, wherein the quantizing circuit comprises:

a combination circuit configured to combine the first signal with an analog feedback signal to produce a delta signal;

an integrator configured to receive and integrate the delta signal to produce a sigma signal; and

an analog-to-digital converter configured to receive the sigma signal and compare the sigma signal with a reference signal to produce a digital output signal.

**2.** The device of claim **1**, comprising a filter coupled to the quantizing circuit, wherein the filter is configured to receive the digital output and generate a value associated with the first signal based on the digital output.

**3.** The device of claim **1**, wherein the quantizing circuit comprises a digital-to-analog converter configured to convert the digital output signal to the analog feedback signal.

**4.** The device of claim **3**, wherein the digital-to-analog converter comprises a current source and a switch.

**5.** The device of claim **1**, wherein the integrator comprises a capacitor.

**6.** The device of claim **1**, wherein the analog-to-digital converter comprises a comparator.

**7.** The device of claim **1**, wherein the combination circuit comprises a first voltage to current converter configured to convert the analog input signal to an analog input current.

**8.** The device of claim **7**, wherein the combination circuit comprises a second voltage to current converter configured to convert the analog feedback signal to an analog feedback current.

**9.** The device of claim **7**, wherein the first voltage to current converter comprises a transistor in series with a resistor.

**10.** A device, comprising:

a resistive memory array comprising a plurality of storage locations; and

a quantizing circuit, wherein the quantizing circuit comprises:

a combination circuit configured to combine an analog input signal related to a value stored in a data storage location of the plurality of storage locations, with an analog feedback signal to produce a delta signal;

an integrator configured to receive and integrate the delta signal to produce a sigma signal;

an analog-to-digital converter configured to receive the sigma signal and compare the sigma signal with a reference signal to produce a digital output signal; and

a digital-to-analog converter configured to convert the digital output signal to the analog feedback signal.

21

11. The device of claim 10, wherein the resistive memory array comprises a phase change memory array or a magnetoresistive memory array.

12. The device of claim 10, comprising control circuitry configured to receive command signals from a processor and to assert a clock signal within the memory device. 5

13. The device of claim 12, comprising a filter coupled to the quantizing circuit, wherein the filter is configured to receive the digital output and generate a value associated with the analog input signal based on the digital output. 10

14. The device of claim 13, wherein the filter is configured to receive the clock signal and generate a value associated with the analog input signal utilizing the clock signal.

15. The device of claim 10, wherein the digital-to-analog converter comprises a switch configured to selectively route a reference current to ground or to conductor coupled to the data storage location based on the digital output signal to generate the analog feedback signal.

16. The device of claim 10, wherein the digital-to-analog converter comprises a switch coupled to a capacitor, wherein the switch is configured to selectively supplement a reference current with current from the capacitor based on the digital output signal to generate the analog feedback signal. 20

17. A method of sensing a memory element in a system, the method comprising:

22

providing, from a processor, a read command signal to a phase change memory device or a magnetoresistive memory device;

determining, in a quantizing circuit of the memory device, a difference between a reference voltage and a voltage of an electrical conductor connected to a resistive memory element of the phase change memory device or the magnetoresistive memory device, wherein determining the difference comprises converting a voltage signal into a current signal;

integrating, with an integrator of the quantizing circuit, the difference over time to determine a sum; and controlling the voltage of the electrical conductor by selectively conducting a reference current through the electrical conductor based on the sum.

18. The method of claim 17, wherein determining the difference comprises generating the reference voltage by mirroring a current onto the electrical conductor.

19. The method of claim 17, wherein controlling comprises processing the reference current with a low-pass filter.

20. The method of claim 17, wherein determining a difference between a reference voltage and a voltage of an electrical conductor comprises determining a difference between the reference voltage and a bit-line voltage.

\* \* \* \* \*